

Dial 0 for mailbox options

Main Menu

Voice Mail lets callers leave recorded messages for you and lets you leave recorded messages for co-workers. Messages get stored in each person's mailbox. To listen to your messages or use other Voice Mail features, call your mailbox and access the Main Menu. **Your Message Wait LED flashes (red) when you have a message.** **Automated Attendant** answers your company's calls with a recorded message and gives dialing instructions for callers to follow.

[Soft Key]

L Listen to Messages [Lstn] 5

While listening you can:

RE	Record RE ply [N/A]	73	L	Listen to Next Msg [Next]	5	1S	Select Saved Message List	17
MF	Have M sg F orwarded [N/A]	63	B	B ackup a Few Secs	2	1A	Select All Message List	12
MC	Make C all to Sender [N/A]	62	BB	B ackup to B eginning [Rpt]	22	#	Exit Listen Mode [Exit] - [Exit]	#
TI	Get T ime, Date	84	G	G o Ahead a Few Secs	4		Select the Listen Mode See also 'Select Listen Mode' on the Main Menu	
SA	S Ave Message	72	*	Pause/Resume Listening [N/A] [N/A]	*			
E	E rase Msg [Erase]	3	1N	Select New Message List	16			

RS Record & Send Message [Rec] 77

Enter mailbox number, then:

While recording you can:

*	Renter mailbox number [MBOX]	*	*	Pause/Resume [Pause] [Resume]	*
#	Start Recording [Cont]	#	E	E rase Recording [Cnc]	3
	Exit to Main Menu [Exit]		#	E nd Recording [Done]	#

G Mailbox Greeting [Greet] 4

Callers hear your active greeting (1-3) only if you do not answer or are busy. If Auto Attendant DND is ON, the Auto Attendant does not ring your phone. Callers immediately hear your active greeting. If OFF, the Auto Attendant will try your extension.

Calling Your Mailbox and Accessing the Main Menu

To call your mailbox from outside the company:

- Dial company phone number _____.
- Wait for Automated Attendant to answer.
- Dial # and your mailbox number.
 - Optionally dial * and co-worker's mailbox number to leave a message.
 - The codes in your system may be different.

To call your mailbox from your extension:

- Press MSG.
 - From a single line extension, lift handset and dial * 8 instead.

To access a feature from your mailbox Main Menu:

- Dial the letters shown to the left of the feature name.
 - The corresponding numbers are shown to the right.
 - The letters you dial match some of the letters in the feature name.

RN Record Mailbox Name 76

InMail will play your mailbox name in the voice prompts instead of your mailbox number.

OP Mailbox Options 67

The mailbox options are:

TI	T ime and Date	84
SA	S ys A dmin Options (For Admin Mailboxes only)	72
1N	Select Listen Mode	16
1S	Select New Message List	17
1A	Select Saved Message List	12

These options are also available while listening to a message.

S	S ecurity Code [Sec]	7
N	Changes or erases your mailbox security code.	
N	M essage N otification [Notif]	6
AT	Calls co-worker or outside number when you get msg.	
AT	A uto T ime Stamp [Time]	28
#	Plays the msg time, date and sender after the msg.	
#	Exit Menu [Exit]	#

Setup personal greeting:
Press VSMG
Press Greet
Press GR1
Listen to the options and record greeting

X Exit Mailbox 9